



EXIT DEVICE – XMS

Features

- Passive Infrared
- 12 OR 24 VDC
- Indoor use only
- Low current draw 20-50 mA depending on switching status
- Specifically designed to reliably release magnetic locks

Operating Temperature
0 to 43C [32 to 110F]

How to Order

<u>Part #</u>	<u>Description</u>
XMS	Exit Motion Sensor



Architectural Specifications

- The Exit Motion Sensor shall be produced by an ISO 9001 certified manufacturer.
- The exit device shall employ passive infrared detection to initiate door release and shall operate on 12 or 24 volt DC.
- The device shall have an adjustable detector face to allow for precise pattern configurations, and easy pattern adjustment.
- The exit device shall have a SP/DT relay output for shunting the alarm or access control system and field effect transistor for direct control of an electromagnetic lock.
- The relay shall operate 50 milliseconds before the transistor to suppress false alarms.
- Wiring is via labeled screw terminals.