



Overview

- This power supply/charger converts a low voltage AC input into 6VDC, 12VDC or 24VDC @ 2.5 amp continuous supply current. This unit has a wide range of applications for access control, security and CCTV system accessories that require additional power.

Specifications

- | | |
|---|---|
| <ul style="list-style-type: none"> • 6VDC, 12VDC or 24VDC selectable output. • 2.5 amp supply current. • Input - Altronix transformers:
For 6VDC or 12VDC applications use TP1640.
For 24VDC applications use T2885. • Filtered and electronically regulated output. • Short circuit and thermal overload protection. • Battery short circuit protection (circuit breaker). • Built-in charger for sealed lead acid or gel type batteries. | <ul style="list-style-type: none"> • Maximum charge current .3 amp. • Automatic switch over to stand-by battery when AC fails. • AC input and DC output LED indicators. • Extremely compact design. • Includes battery leads. • Snap Trac compatible (order Altronix model number ST3). |
|---|---|

Board Dimensions (approximate)

3.5"L x 3"W x 2"H

