

MLRK1-FAL25

(Formally FLP-UL-M-KIT)

- **PUSH TO START (PTS) TECHNOLOGY**
- **FAST, QUIET, SMOOTH**
- **UL LISTED**
- **BUILT-IN REQUEST TO EXIT**
- **FULL PUSH PAD RETRACTION FOR TRUE ELECTRONIC DOGGING**



The **FLP-UL-M-Kit** is a practical and cost-effective way to convert a mechanical Falcon 24/25 series device to an electrified latch pullback device. Our easy-to-install motor-driven kit installs in a matter of seconds with no drilling or screws required, a true “drop-in” kit! **PTS** allows for an easy post-installation adjustment of the latch/latches. A built-in REX switch is standard on all units! Last but not least, features an updated **MM4S** module with 2 different energy consumption settings from energy conscious to high torque to get the tough jobs done!

SPECIFICATIONS

Voltage:

- Voltage range – 22 to 28 VDC
- System protection – unit shutdown when voltage exceeds 28VDC
- Standard - Average Current Peak: 900mA, Average Current Hold: 215mA
- High Torque - Average Current Peak: 2A, Average Current Hold: 250mA
- PTS adjustment – approx. 1/4”

Wire Run:

- 300’ with 18ga wire

Product Details:

- Weight: 2 Lbs

Device Cutdown Details:

- 36” - 2”
- 48” - 8”

Features:

- Next Generation MM4S Smart Module: On board diagnostics with audible feedback for adjustment and power issues
- “PTS”: 5 second electronic adjustment for easy post installation adjustment
- Electric dogging rated for continuous duty - Auto re-engage if push pad is pulled from dogged position
- Low Current Draw - Field switchable to “High Torque” mode
- Up to 300’ wire run with 2-18ga wire - Long wire runs provides installer with convenience of placing the Command locking hardware power supply in a centralized location; i.e. the same closet as the access control panel
- 8’ cable with Quick Molex Connect for MM4S module to easily connect to power supply lead
- Request-to-Exit built-in standard
- 3-year “no hassle” warranty

Accessories: Additional Charge

 REXKIT-ED - Built-in REX ships standard

HOW TO ORDER

Part #	Easy Order #	Description
MLRK1- FAL25 (formally FLP-UL-M-KIT)	79338	Kit w/ REX for the Falcon 24/25. EU 24 VDC.

MLRK1-FAL25 MATRIX

The KIT will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.

Falcon Kit	Mechanical unmodified	CAT Modified Motor	Falcon Solenoid (EL)	SDC Motor (LR100-FRK)	ACSI Motor (1550-MDF)
MLRK1-FAL25	24/25 ✓	✓	✓	✓	✓

NEED A LOCKING HARDWARE POWER SUPPLY?

RECOMMENDED LOCKING HARDWARE POWER SUPPLIES:

- PS204/PS204B
- PS220/220B
- PS480B
- PS210
- PS440B



CA Customer Support 855-823-3002 | www.commandaccess.com | US Customer Support 888-622-2377

Command Access is not a licensee, or affiliated, associated or connected with Allegion, Assa Abloy, Stanley, Schlage, Falcon, Von Duprin, Dorma, Sargent, Corbin Russwin, Yale, Emtek, Adams Rite, Best, Precision, Arrow, Design Hardware, Cal Royal, Jackson, Kawneer, AHT, Marshall Best, Marks, Accurate, Baldwin, FSB, PDQ, Lawrence, Trans Atlantic, Hager, LSDA, General Lock, or Omnia or any of their subsidiaries or affiliates.